

# marantz®

## SR5011

### 7.2 CHANNEL NETWORK AV RECEIVER WITH BLUETOOTH AND WI-FI



PANDORA

((SiriusXM))



Packed with the latest audio and video technologies, the Marantz SR5011 lifts your Home Theater to a new level. Featuring Dolby Atmos and DTS:X (via firmware update), you can enjoy breathtaking 3D surround sound with today's advanced movie soundtracks. The SR5011 is made out of carefully selected, high grade audio components and Marantz-own HDAMs (Hyper Dynamic Amplifier Module), delivering the renowned Marantz Hi-Fi and Home Theater sound. The amplifier section delivers 100 Watts of output, enough to fill even bigger rooms, and thanks to advanced Audyssey MultEQ XT, tailored perfectly to your individual listening room.

#### Highlights

- 7.2 channel AV Receiver with 100 watts per channel (8ohms, 20 Hz~20 kHz, 0.08% THD)
- Built-in WiFi with 2.4GHz/5GHz dual band support; built-in Bluetooth
- 4K/60 Hz full-rate pass-through, 4:4:4 color resolution, HDR and BT.2020
- 8 HDMI inputs (incl. 1 front) with full HDCP 2.2 support; 2 HDMI outputs
- Analogue to HDMI conversion and SD/HD to 4K Upscaling
- Dolby Atmos (up to 5.1.2) and DTS:X (via firmware update)
- AirPlay, Bluetooth, Internet Radio, Spotify Connect, Pandora, SiriusXM, Network Audio Streaming
- DSD (2.8/5.6MHz), FLAC, ALAC, AIFF and WAV support
- Audyssey MultEQ XT, Dynamic Volume and Dynamic EQ
- Color-coded speaker terminals, Setup Assistant, Marantz 2016 AVR Remote App
- Intelligent ECO mode with off/on/auto setting
- Advanced Multi-Room options; 7.2ch Pre-out; RS232 Control

#### Your Benefits

- Enough power to fill bigger rooms with renowned Marantz sound
- Improved network stability especially in WiFi-crowded homes
- Latest HDMI standard for future-proof compatibility
- Extended connectivity: ready to feed a TV and projector in parallel
- HD video quality from existing DVDs or analogue sources
- Immersive 3D sound with effects from overhead
- Access to almost unlimited online music sources
- High Resolution audio streaming, even gapless
- Delivering perfect equalization for your individual room
- Hassle-free installation, setup and operation
- Energy-conscious without compromising on performance
- Audio and video in multiple rooms; ready for 3rd Party Home Automation systems



## SR5011 7.2 CHANNEL NETWORK AV RECEIVER WITH BLUETOOTH AND WI-FI



Design and specifications are subject to change by Marantz without notice.

FEATURES	SR5011
<b>MULTICHANNEL SURROUND</b>	
DTS HD Master / DTS:X / DTS Neural:X	• / • / • (firmware update)
Dolby TrueHD / Dolby Atmos / Dolby Surround	• / • / •
Multichannel Stereo	•
Compressed audio Enhancer: MDAX2	•
<b>NETWORK / SOURCES</b>	
Network Audio Streaming	•
Lossy formats MP3 / WMA / AAC	• / • / •
Lossless formats FLAC / ALAC / WAV	• / • / •
DSD Streaming	• (2.8 MHz / 5.6 MHz)
FLAC HD 192/24 / WAV 192/24 / ALAC 96/24	• / • / •
Gapless playback	• (FLAC, WAV, ALAC, DSD)
AirPlay audio streaming	•
Internet Radio (vTuner)	•
Spotify Connect / Pandora / SiriusXM*	• / • / •
Compatible with Remote APP	Android/iOS/Kindle
Ethernet / Wi-Fi	• / • (dual antenna / dual band)
Network: (IP-control / update)	• / •
Front Inputs: HDMI / USB	• / •
USB Audio / Made for iPod / Made for iPhone	• / • / •
FM / AM Tuner	• / •
Bluetooth	•
<b>HDMI</b>	
4K 60Hz 4:4:4 resolution / HDCP 2.2	• / •
HDMI pass through on stand-by	•
3D video pass through	•
Video conversion	CVBS / HDMI; Comp / HDMI
Video processing and -scaling	1080p, 4K 30/25/24Hz
<b>INPUTS/OUTPUTS</b>	
<b>VIDEO</b>	
Composite In / Out	2+1 / 1
Component In / Out	2 / 1
HDMI In / Out	7+1 / 2

\* This feature is not available in all countries.

<b>AUDIO</b>	
Analogue In / Out	4+1 / 0
Digital Optical In	2
Digital Coaxial In	2
Multichannel Pre Out	• (7.2)
Zone audio preout	•
Subwoofer Out	2
7.1 Multichannel input	•
<b>SPECIFICATIONS</b>	
Number of poweramps	7
Power Output per channel	
Maximum Power Output Per Channel	200 W
6 ohm, 1 kHz, 0.7%, 2ch Drive	140 W
8 ohm, 20 Hz - 20 kHz, 0.08%, 2ch Drive	100 W
Audio Signal to Noise Ratio	100 dB
<b>GENERAL</b>	
Available colours: Black / Silver-Gold	• / •
System Remote Control	RC024SR
Power Consumption in W	650
Power Consumption No-Sound (ECO ...on/off) in W	45 / 75
Standby Consumption in W	0.2 (with CEC 0.5)
Maximum Dimensions (W x D x H) in mm	17.3 x 13.6 x 6.3
Weight in LBS	22.1
<b>EAN</b>	
NA SR5011/U1B	699927150853
	Black

The Bluetooth® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by D&M Holdings Inc. is under license. Dolby, Dolby Atmos, and the double-D symbol are trademarks of Dolby Laboratories. DTS, the Symbol, DTS in combination with the Symbol, DTS:X, and the DTS:X logo are registered trademarks or trademarks of DTS, Inc. in the United States and/or other countries. The Spotify software is subject to third party licenses found here: [www.spotify.com/connect/third-party-licenses](http://www.spotify.com/connect/third-party-licenses). Other trademarks and trade names are those of their respective owners. Marantz is a trademark or registered trademark of D&M Holdings, Inc.

\* All specs can be subject to change.

[V01]